tehnotzka

https://tehnoteka.rs

Uputstvo za upotrebu (EN)

GEMBIRD konverter USB 3.0 (m) na S-Video (ž) + 3xRCA (ž) Videograbber





Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

https://tehnoteka.rs/p/gembird-konverter-usb-30-m-na-s-video-z-3xrca-z-videograbberakcija-cena/

VIDEOGRABBER UVG-002

1	Installation videograbber
2	If Windows doesn't automatically install the grabber
3	Installation for possibly a driver
4	Download OBS studio for digitizing
5	Add video source in OBS studio
6	Explanation of no image
7	Explanation of no sound
8	Support OBS studio
9	Free program video editing

1. In most cases, WINDOWS 10 does not require the use of a separate driver. In the best case, your Windows system immediately sees the videograbber and does the installation automatically.

You will then get when inserting the videograbber into a USB port a sound from Windows that something is being connected and the installation will proceed automatically.

Your computer must be connected to the Internet and automatic installation must be allowed on your computer.

2. If your computer does not see a videograbber, you can use these "drivers" for this, but it is advisable (because of the latest drivers) to leave the installation to Windows yourself.

If your computer has equipped the grabber itself with the installation, you can proceed to step 4

Honestech "driver: you can download here. https://gmb.nl/Repository/7998/UVG-002_driver_233E0F02-F8B4-4A6A-9D3C-34BEDD302A8C.zip

Please note, it is a ZIP file, you must first "extract" the files before use. If you are not familiar with unzipping, you can find an explanation via this link from Microsoft: <u>https://support.microsoft.com/nl-nl/windows/bestanden-zippen-en-uitpakken-8d28fa72-f2f9-712f-67df-f80cf89fd4e5</u>

The included CD ROM is only for older Windows versions up to and including Windows 7.

3. Double click on new drive for UVG-002

Bestand Opdrachten Extra Favor	4A6A-9D3C-34 ieten Opties	4BEDD302A8C Help	(1).zip (Evaluatiekop	ie)			
	Warran	Vanuiidaran				Ð	E V
Toevoegen onpakken in Testen	2-F8B4-4464-(30248C (1) zin - 7IP a		kelijke groott	a 116 766	820 hutes
Naam	Ğrc	ootte Ing	epakt Type File folder	Gewijzi	gd Cl	RC32	
new drive for UVG-002			File folder	6/21/20	016 8:23		
Double click on an UVG-002_driver_233E0F02-F8B4-4A6	utorun.exe 5A-9D3C-34BED	e applicati D302A8C (1).zi	on p (Evaluatiekopie)				
Double click on an UVG-002_driver_233E0F02-F8B4-4AG estand Opdrachten Extra Favoriete	5A-9D3C-34BED n Opties Hel, eergeven Verw	e applicati D302A8C (1).zi p ijderen Zoeke	p (Evaluatiekopie)	Viruscontrole	Commentaar	SFX	
Double click on an UVG-002_driver_233E0F02-F8B4-4A6 estand Opdrachten Extra Favoriete Importante Extra Favoriete Toevoegen Uitpakken in Testen W Toevoegen Uitpakken in Testen W	A-9D3C-34BED n Opties Hel ergeven Verw IB4-4A6A-9D3C	e applicati DD302A8C (1).zi p ijderen Zoeke -34BEDD302A8	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info 3C (1).zip\new drive for	Viruscontrole r UVG-002 - ZIP ar	Commentaar rchief, oorspro	SFX SFX	rootte 116,766,820 t
Double click on an UVG-002_driver_233E0F02-F8B4-4A6 estand Opdrachten Extra Favoriete itoevoegen Uitpakken in Testen W UVG-002_driver_233E0F02-F8 aam	sA-9D3C-34BED n Opties Hel eergeven Verw 184-4A6A-9D3C Grootte	e applicati DD302A8C (1).zi p ijderen Zoeke -34BEDD302A8 Ingepakt	p (Evaluatiekopie) p (Evaluatiekopie) Wizard Info Info Info Info Info Info Info Info Info Info Info Info	Viruscontrole r UVG-002 - ZIP ar Gewijzigd	Commentaar rchief, oorsprc CRC32	SFX SFX	rootte 116,766,820 b
Double click on an UVG-002_driver_233E0F02-F8B4-4A6 estand Opdrachten Extra Favoriete Uitpakken in Testen W UVG-002_driver_233E0F02-F8 aam	sA-9D3C-34BED n Opties Hel eergeven Verw 184-4A6A-9D3C Grootte	e applicati DD302A8C (1).zi p nijderen Zoeke -34BEDD302A8 Ingepakt	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info SC (1).zip\new drive for Type File folder File folder	Viruscontrole r UVG-002 - ZIP ar Gewijzigd 6/21/2016 10:4.	Commentaar rchief, oorspro CRC32	SFX SFX	rootte 116,766,820 t
Double click on an UVG-002_driver_233E0F02-F8B4-4A6 estand Opdrachten Extra Favoriete Uitpakken in Testen W UVG-002_driver_233E0F02-F8 aam	sA-9D3C-34BED n Opties Hel eergeven Verw 184-4A6A-9D3C Grootte	e applicati DD302A8C (1).zi p ijjderen Zoeke -34BEDD302A8	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info BC (1).zip\new drive for Type File folder File folder File folder File folder	Viruscontrole r UVG-002 - ZIP ai Gewijzigd 6/21/2016 10:4. 6/21/2016 8:23	Commentaar rchief, oorsprc CRC32	SFX SFX	rootte 116,766,820 t
Double click on an UVG-002_driver_233E0F02-F8B4-4AG estand Opdrachten Extra Favoriete Toevoegen Uitpakken in Testen W ↑ UVG-002_driver_233E0F02-F8 Aaam Drivers AutoPlay autorun.exe	sA-9D3C-34BED n Opties Hel eergeven Verw 3B4-4A6A-9D3C Ğrootte 2,830,336	e applicati DD302A8C (1).zi p nijderen Zoeke -34BEDD302A8 Ingepakt	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info BC (1).zip\new drive for Type File folder File folder File folder File folder File folder File folder File folder	Viruscontrole r UVG-002 - ZIP ai Gewijzigd 6/21/2016 10:4. 6/21/2016 8:23 6/20/2016 10:4.	Commentaar rchief, oorspro CRC32	SFX srkelijke g	rootte 116,766,820 t
Double click on an UVG-002_driver_233E0F02-F8B4-4AG estand Opdrachten Extra Favoriete Toevoegen Uitpakken in Testen W ↑ Image: UVG-002_driver_233E0F02-F8 laam Drivers AutoPlay UVG-002_driver_233E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_234E0F02-F8 UVG-002_driver_24F0-F8 UVG-002_F8 UVG-002_F8	utorun.exe 5A-9D3C-34BED n Opties Hel eergeven Verw 3B4-4A6A-9D3C Ğrootte <u>2,830,336</u> 1,991,311	e applicati DD302A8C (1).zi p ijjderen Zoeke -34BEDD302A8 Ingepakt	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info 3C (1).zip\new drive for Type File folder File folder File folder File folder File folder Microsoft Edge PD	Viruscontrole r UVG-002 - ZIP ai Gewijzigd 6/21/2016 10:4. 6/21/2016 8:23 6/20/2016 10:4. 6/20/2016 10:4.	Commentaar rchief, oorsprc CRC32	SFX SFX	rootte 116,766,820 t
Double click on an UVG-002_driver_233E0F02-F8B4-4AG estand Opdrachten Extra Favoriete Toevoegen Uitpakken in Testen W ↑ IMUG-002_driver_233E0F02-F8 Jaam - Drivers AutoPlay Jutorun.exe Video Grabber user-manual.pdf SN.txt	utorun.exe 5A-9D3C-348ED n Opties Hel leergeven Verw 384-4A6A-9D3C Ğrootte 2,830,336 1,991,311 29	e applicati DD302A8C (1).zi p ijjderen Zoeke -34BEDD302A8 Ingepakt 1,300,956 1,935,620 31	p (Evaluatiekopie) p (Evaluatiekopie) wizard Info ac (1).zip\new drive for Type File folder File folder File folder File folder Microsoft Edge PD Text Document	Viruscontrole r UVG-002 - ZIP ai Gewijzigd 6/21/2016 10:4. 6/21/2016 8:23 6/20/2016 10:4. 6/20/2016 10:4. 3/24/2011 12:1.	Commentaar rchief, oorspro CRC32 	SFX SFX onkelijke g	rootte 116,766,820 t

Give permission when notifying Windows

Next, the installation screen should appear



After installation, restart pc.

Serial number requested is in this document

UVG-002_driver_233E0F02-F8B4-4A6A-9D3C-34BEDD302A8C (1).zip (Evaluatiekopie)

Bestand Opdrachten Extra Favoriet	en Opties Help					
Toevoegen Uitpakken in Testen V	Veergeven Verwijder	en Zoeke	n Wizard Info	Viruscontrole	Commentaar	SFX
1 UVG-002_driver_233E0F02-F	884-4A6A-9D3C-34B	EDD302A8	C (1).zip\new drive for	UVG-002 - ZIP ar	chief, oorspror	nkelijke grootte 116,766,82
Naam	Grootte	Ingepakt	Туре	Gewijzigd	CRC32	
📜 4			File folder			
Drivers			File folder	6/21/2016 10:4.		
AutoPlay			File folder	6/21/2016 8:23		
🔳 autorun.exe	2,830,336	1,300,956	Application	6/20/2016 10:4.	. 4559DD6D	
📾 Video Grabber user-manual.pdf	1,991,311	1,935,620	Microsoft Edge PD	6/20/2016 10:4.	. 03DA00A3	
SN.txt	29	31	Text Document	3/24/2011 12:1.	. DD0288A8	
autorun.inf	29	29	Setup Information	6/20/2016 10:4.	. E9556206	

To make it easy I already have the serial number here:

TVR25-NMBGG-HGGGH-362DC-6BMG6

4. Download OBS studio for your Windows system

You can download it for free on <u>www.obsproject.com</u>

On our youtube channel a video with explanation: https://www.youtube.com/watch?v=TX6JDPjQ4M0&feature=emb_logo_

> Install OBS studio, and then restart the computer . When the computer has restarted , open the OBS app on your computer.



5. Add videograbber in OBS studio (there are several videos with explanations of OBS studio on Youtube) :

Press the + at sources:



Choose Video recording device:

				Afbeelding		
			$\mathbf{\Psi}$	Audioinvoer Opname		
			()	Audiouitvoer Opname		
			Ţ	Beeldschermcapture		
			Ø	Browser		
			3	Diashow		
			æ	Gamecapture		
			^و	Kleurbron		F
Geen bron g	geselecteerd		►	Mediabron		te
	Scènes	6		Scène		
Scene			T	Tekst (GDI+)		to
				Vensteropname		P
				Video opname-apparaat		
				Groep		\u
				Verouderd	•	
+ -	\sim		- T	- ¥ / Y		

Here you enter a name for your Video File and click OK:

S Maak/Selecteer Bron		×
O Nieuwe maken		
NAAM VOOR VIDEO		
Bestaande toevoegen		
✓ Maak bron zichtbaar		
	ОК	Annuleren

Here you choose OEM or AV TO USB2.0 (varies by connected device)

Apparaat	HD Webcam HD Webcam AV TO USB2.0 OBS Virtual Camera Video Instellen Crossbar Instellen	÷
	Crossbar Instellen Deactiveer wanneer niet zichtbaar	
Deactiveer wanneer niet zichtbaar Resolutie/FPS Type Standaard van apparaat		
Resolutie		~
	Resolutie/FPS Type Standaard van apparaat \$ Resolutie FP8 Gelijk aan Uitvoer-FPS \$ Wideoformaat Elke \$	
Kleurruimte	Standaard	
Kleurbereik	Standaard	
Bufferen 🕐	Automatisch detecteren	
Standaardwaarden	OK Ann	uleren

Put your connected device on PLAY and you can start digitizing. In OBS, everything can be adjusted to your liking in terms of settings.

Our advice is to first record a small piece to check whether your image and sound has with the recordings.

6. If OBS sees the grabber as OEM or AV 2.0 USB but you don't see an image, check your computer to make sure you have the settings in Windows correctly to give permission to use camera.

1. Klik op het "Start" icoon.



2. Daarna, klik op de "Instellingen" icoon.



3. Open de "Privacy" optie.



4. Aan de linkerkant van het scherm, selecteer "Camera" en schakel deze in zodat de Totalmedia software de machtiging heeft om de video grabber functionaliteit optimaal te gebruiken.



5. Wanneer de Totalmedia software nog actief is op je PC/Laptop, sluit deze dan en start de software opnieuw op of herstart je PC/laptop.

7. IF NO SOUND IN OBS (note, if your device is only connected with the s-video cable you can not have sound because s-video does not let sound through, you should also use a tulip plug for the audio!):

Try the audio input recording option



If that doesn't give any sound either:



Right click in this field of Desktop Audio and Mic/Aux

Olf Stato 2433 (H bit window) -	Partie Untilled - Scenes Untilled					- a ×
The Edit View Profile Score Collec	and the late				12	
_						
			°			
			ar ar			
				and the second se	-0	
				Acres -		
				Copy Clawre		
				Version Lawood	In the sector in the local sector is a sector of the local sector is a sector is a sector of the local sector is a sector is a sector of the local sector is a sector is a sector of the local sector is a sector is a sector is a sector of the local sector is a sector is a sector of the local sector is a sector is a sec	and the local diversion of the local diversio
	Trans Carles Incis	The second secon		then	+-0	First Sectors
		-		Concession in succession		-
+- ~~	+-0 ~~					
100	Dello La		a logal based		OK HIMM NO HIM	ALL DAY A PROPERTY AND A PROPERTY AN
P Type here to search	Fi G				N A 6 2 D 4 9 9	10 1NG 1/M/0020

Then select the Option Advanced Audio Properties from the drop-down menu that appears

Advanced Audio I	Properties											×
Name	Volume		Mono	Balance	Sync Offs	et	Audio Monitoring	Tracks				
Desktop Audio	-6.1 dB	0			0 ms	0	Monitor Off	1 2 2	2 I 🗹	4 🗹	5 5	6
Mic/Aux	0.0 dB	0		i	0 ms	0	Monitor Off	2122	Z 1 🗹	• 🖂	5 2	6
Video Capture Device	0.0 dB	0			0 ms	0	Monitor Off	21 22	2 3 V	4 🗹	5 5	4.6
											c	0549

After that, the sound can be set in 1 of these options. In this screen as it stands now there is no sound. By pressing the arrows next to Monitor Off, something else can be selected. In my case, there is no connected video device.

Information from the Internet:

Monitor

OffWith this option, the audio source is included in the recording or live stream, but you can't monitor it when you're connected with headphones.

Monitor Only (mute output)

This means that you can listen in on this audio source, but it is not recorded. This is a useful feature for the advanced productions.

Monitor and

OutputThis is the function that matters. When you are connected with headphones, you can listen and monitor with this audio source. To avoid 'singing around', it is wise not to use your computer or laptop speakers. Instead, use headphones or earphones.

8. If there are any questions about OBS studio, you can contact them in various ways via their website https://obsproject.com/.

On youtube you can also find many videos about the use of OBS studio:

https://www.youtube.com/results?search_guery=obs+studio+nederlands_

9. Video editing:

If you want to edit the video afterwards , you can download the program Davinci Resolve 17 for free on the internet.

On youtube there are instructional videos to help you edit your videos.

tehnotzka

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda Gembird, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanesenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

https://tehnoteka.rs/p/gembird-konverter-usb-30-m-na-s-video-z-3xrca-zvideograbber-akcija-cena/