

Informacije o proizvodu (EN)

CUDY FS1018PS1 switch

The logo for Cudy, featuring the word "cudy" in a lowercase, rounded, blue sans-serif font.

Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

<https://tehnoteka.rs/p/cudy-fs1018ps1-switch-akcija-cena/>



Model

FS 1018PS1



16-Port 10/100M PoE+ Switch with
2 Gigabit Uplink Ports and 1SFP Slot

Datasheet



Features

- 16* 10/100M PoE Ports + 2*Gigabit Ethernet Uplink Ports + 1* Gigabit SFP Uplink Port;
- Support IEEE802.3, IEEE802.3u, IEEE802.3x, IEEE802.3af / at, store and forward;
- Compatible with IEEE802.3at (30W) and IEEE802.3af (15.4w);
- Ethernet port supports 10/100M adaptive and POE functions;
- Flow control mode: full-duplex adopts IEEE 802.3x standard, half-duplex adopts Back pressure standard;
- Support port auto flip (Auto MDI/MDIX);
- All ports support wire-speed switching;
- Automatically supplied to adaptive devices;
- Panel indicator monitoring status and help failure analysis;
- Support VLAN Mode and Extend 250 meters Mode;
- Support 1U Rack Mount.

Specifications

Model	FS1018PS1
Connector Type	16*10/100M PoE Ports + 2*Gigabit Ethernet Uplink Ports + 1*Gigabit SFP Uplink Port
Network Protocols	IEEE802.3 / IEEE802.3u / IEEE802.3x IEEE802.3ab / IEEE802.3z
PoE Parameters	PoE Standard: IEEE802.3af /IEEE802.3at Max each port: 15.4W (IEEE 802.3af) Max each port: 30W (IEEE 802.3at) PoE compatibility: IEEE 802.3af/at adaptive PoE port output: DC48-55V Power Pin : Power over spare pairs 1/2(+), 3/6 (-)
Network Media	10BASE-T: Cat 6 UTP(≤250 meter) 100BASE-TX: Cat5 or more UTP (≤100 meter) 1000BASE-TX: Cat5 or more UTP (≤100 meter)
Optical	MultiMode Fiber: 850nm, 1310nm, Transmission Distance: 550m/2Km Single-Mode Fiber: 1310nm, 1550nm, Transmission Distance: 20/40/60/80/100/120km
Performance Specification	Bandwidth: 9.2Gbps MAC: 2K Packet Buffer Memory: 3Mbit Packet Forwarding Rate: 6.84Mpps



Specifications

Power Supply	1Power input: AC100-240V 50/60Hz, Output: 52V3.85A, PoE Budget: 180W	
Working Environment	Operating Temperature: -20°C ~ 50°C; Storage Temperature: -40°C ~ 85°C;	
	Operating Humidity: Max 90%, non-condensing Storage Humidity: Max 95%, non-condensing	
	Working Height: Max to 10,000 feet (3,000 meters) Storage Height: Max to 10,000 feet (3,000 meters)	
	Product Dimension (L*W*H): 320*207*45mm Package Dimension (L*W*H): 370*290*85mm N.W: 1.61KG G.W: 2.14KG	
Physical Parameter		
Package Contents	Ethernet Switch: 1 unit User Guide: 1 unit Warranty Card: 1 unit Power Cord: 1unit 1U Rack Mount: 1 pair	
	MTBF	100,000 hours

LED Indicators	PWR (Power indicator), Mode (Dial indicator), 1-19Green (Link&Data), POE Max(PoE Budget Status)
PWR	On: Equipment power on Off: Equipment power off
Mode	On: VLAN Flashing: Extend Off: Default
1-19Green	On: Link connectivity Flashing: Data transmission Off: Link abnormality
1-16Yellow (POE)	On: POE power supply is normal Off: POE not powered
POE Max (Green)	Off: Indicates that PoE power usage is less than 90% Flashing: Indicates PoE power usage of $90\% \leq P \leq 95\%$ On: Indicates PoE power usage of $95\% < P < 100\%$
POE LED button	Dual color light selection: default green (link data), switch yellow light (POE)
Dip switch	VLAN: 1-16 ports are isolated from each other, only transmit data with uplink ports. PoE watchdog is enabled. Default: All ports communicate freely with each other, with a transmission rate of 10M/100M adaptive. PoE watchdog is disabled. Extend: 1-16 ports max transmission distance extend to 250 meters, transmission rate drop to 10M. PoE watchdog is enabled.

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda Cudy, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanесenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

<https://tehnoteka.rs/p/cudy-fs1018ps1-switch-akcija-cena/>