

## Informacije o proizvodu (EN)

CUDY GS1028PS2 switch

cudy



Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

<https://tehnoteka.rs/p/cudy-gs1028ps2-switch-akcija-cena/>



Model

# GS 1028PS2



24-Port Gigabit PoE+ Switch with 2 Gigabit SFP Ports

Datasheet



## Features

- Support 24\* 10/100/1000M PoE Ports++2\* Gigabit SFP Ports.
- Support IEEE802.3, IEEE802.3u, IEEE802.3x, IEEE802.3ab, IEEE802.3z.
- Ethernet Ports support 10/100/1000M self- adaptive.
- Supports automatic port flipping (Auto MDI/MDIX).
- Adopting a storage and forwarding exchange mechanism.
- All ports support line speed switching.
- 1U rack installation.
- Panel indicator monitoring status and help failure analysis.
- Equipped with a three speed one button intelligent dial switch, supporting VLAN, Default, and Extend modes.
- Support port surge protection: Common Mode 4KV, Differential Mode 2KV( Class B), ESD: Air 8KV, Contact 6KV (Class C).

## Specifications

Power Input	AC100-240V / 50-60Hz
Ethernet	24* 10/100/1000M PoE Ports 2* Gigabit SFP Ports
Bandwidth	52Gbps
Packet Forward Rate	38.68Mpps
Package Cache	4Mbit
MAC Address	8K
Forwarding Mode	Store and forward
Network Protocol	IEEE 802.3: Ethernet Media Access Control (MAC) Protocol IEEE 802.3i: 10BASE-T Ethernet IEEE 802.3u: 100BASE-TX Fast Ethernet IEEE 802.3ab: 1000BASE-T Gigabit Ethernet IEEE 802.3z: 1000BASE-X Gigabit Ethernet (Fiber Optic) IEEE 802.3x: Flow Control
Industry Standard	EMS: EN61000-4-2 (ESD) EN61000-4-5 (Surge)
Network medium	10Base-T: Cat 3, 4, 5 Class or above UTP/STP (≤ 100m) 100Base-TX: Cat 5 Class or above UTP/STP (≤ 100m) 1000Base-TX: Cat 5 Class or above UTP/STP (≤ 100m)
Optical Medium	Multi mode optical fiber: 50/125, 62.5/125, 100/140um Single-mode optical fiber: 8/125, 8.7/125, 9/125, 10/125um



# Specifications

<b>Working Environment</b>	Working temperature: -10~50°C Storage temperature: -40~70°C Working humidity: 10%~90%, non-condensing Storage humidity: 5%~95%, non-condensing
<b>Indicator</b>	PWR (Power Indicator), 1000M (Link Light), Act (Link&Data Link)
<b>PWR</b>	On: Powered on Off: Powered off
<b>1-27 Green</b>	On: Link normal Flashing: Data transmitting Off: Link blocked
<b>1-24 Yellow (POE)</b>	On: POE powered on Off: POE powered off
<b>POE Max (Green)</b>	Off: Indicates PoE power usage is less than 90% Flashing: Indicates PoE power usage of $90\% \leq P \leq 95\%$ On: Indicates that PoE power usage is at $95\% < P < 100\%$
<b>VLAN</b>	Port isolation, ports 1-22 achieve isolation of monitoring, can only communicate with the ports 23-26, to protect internal network security.
<b>Default</b>	Normal mode, all ports can communicate with each other, transmission distance is within 100m, transmission rate is 10/100/1000M self-adaptive.

<b>Extend</b>	Link extend mode, PoE power supply and data transmission distance of ports 17-24 can be extended to 250m, but the transmission rate will down to 10M.
<b>Structure Size</b>	Product Dimensions: 440*204*44mm Package Dimensions: 500*290*85mm Product N.W: 2.82KG Product G.W: 3.38KG
<b>Packing Info</b>	Carton Dimensions: 520*445*310mm Packing Quantity: 5 PCS Packing Weight: 17.5KG
<b>Power Voltage</b>	Input Voltage: AC 100-240V 50/60Hz Supply Power: 52V 5.76A 300W
<b>Power Consumption</b>	Product power: 18.379W POE power: 286.46W
<b>Package List</b>	Switch 1 pc; Power cord 1 pc; User manual 1 pc; Certification 1 pc; Rack ear 1 pair

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda Cudy, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanесenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

<https://tehnoteka.rs/p/cudy-gs1028ps2-switch-akcija-cena/>