# tehnot≡ka

# Informacije o proizvodu (EN)

HP multifunkcijski štampač LaserJet MFP M141a (7MD73A)



Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

https://tehnoteka.rs/p/hp-multifunkcijski-stampac-laserjet-mfp-m141a-7md73a-akcija-cena/

## HP LaserJet MFP M141 Printer series



### Efficient performance from HP's smallest multifunction laser.

An efficient, high-quality multifunction printer that fits your space and your budget. Get fast printing from HP's smallest laser, plus the time-saving HP Smart app. 1,2 Count on professional-quality laser printing and seamless setup.





This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

### Highlights

- · HP's smallest MFP laser in its class
- · Print, scan, and copy with one compact device
- Quality and reliability you expect from industry leader
- Print speed up to 20 ppm
- · Intuitive, easy to use
- HP Auto-On/Auto-Off technology
- ID copy and icon LCD display









#### HP's smallest multifunction LaserJet

- Efficient performance from HP's smallest multifunction laser.
- Business doesn't need to wait for your printer. Maximise your uptime with print speeds up to 20 ppm in A4.<sup>3</sup>
- Smartly and elegantly designed, so it's simple and intuitive to use.
  - Easily handle tasks and get a lot from one device print, scan, and copy.

#### Productivity from your phone

- Get high-quality scanning, and share to Dropbox, Google Drive or cloud from your phone with HP Smart app.<sup>1</sup>
- Access and print documents from your phone with HP Smart app, even from Dropbox and Google Drive.<sup>1</sup>
- With HP Smart app, take a photo as a copy, and send it to your printer from your smartphone.<sup>1</sup>
- Eliminate steps in repetitive tasks with Shortcuts.<sup>1</sup> Scan to the cloud, email, and more in
  just a tap.<sup>1</sup>

#### Trusted quality and convenience

- Count on getting consistently superb prints from a small laser, using Original HP Toner Cartridges
- Simple setup with HP Smart app. It guides you through each step to seamlessly connect from any device.<sup>1</sup>
- Get connected and start printing. Easily connect your printer to your computer with the built-in USB port.<sup>4</sup>
- Start printing right away. The simple LED with buttons helps you complete projects quickly and easily

#### Help save resources without sacrificing performance

- HP Auto-On/Off Technology intelligence can turn your printer on when you need it and off when you don't.<sup>5</sup>
- This HP LaserJet meets ecolabel requirements, including BLUE ANGEL.

## **Product walkaround**

### HP LaserJet MFP M141a Printer shown

- 1. Intuitive control panel
- 2. World's smallest laser in its class
- 3. Letter-size flatbed scanner
- 4. Easy ID copy



## Series at a glance





Model	HP LaserJet MFP M141a Printer	HP LaserJet MFP M141w Printer
Product number	7MD73A	7MD74A

## Configurable Items, Accessories, Supplies and Support

Supplies	W1500A HP 150A Black Original LaserJet Toner Cartridge (~975 pages)
Service and Support	UG206E HP 3 year Care Pack with Standard Exchange for LaserJet Printers UG086E HP 3 year Care Pack with Next Day Exchange for LaserJet Printers UG289E HP 3 year Care Pack with Return to Depot Support for LaserJet Printers (UG206E: all EMEA countries, except ME, Africa, South Africa, Israel, Turkey, UG086E: Austria, Belgium, Denmark, Finland, France, Germany, Ireland, Italy, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland, UK, Czech, Greece, Hungary, Poland, Slovakia, UG289E: ME, Africa, South Africa, Israel, Turkey)

## Technical specifications

Model	HP LaserJet MFP M141a Printer	HP LaserJet MFP M141w Printer	
Product number	7MD73A	7MD74A	
Functions	Print, copy, scan		
Control panel	3 LEDs (Toner. Attention, Ready); 3 buttons (Cancel, Copy, Power)	8 buttons (Power, Cancel, Copy, ID Copy, Wireless, Copy setting, Up, Down), 4 LEDs (Ready/Power, Error, Toner, Wireless)	
Print	•	•	
Print technology	Laser		
Print speed <sup>1</sup>	Black (A4, normal) Up to 20 ppm;		
First page out <sup>2</sup>	Black (A4, ready): As fast as 8.5 sec; Black (A4, sleep): As fast as 9.1 sec;		
Print resolution	Black (best): Up to 600 x 600 dpi; Technology: HP FastRes 600;		
Monthly duty cycle	Up to 8,000 pages A4; Recommended monthly page volume: 100 to 1000		
Printer smart software features <sup>3,4</sup>	HP Auto-On/Auto-Off <sup>1</sup> , HP Smart App <sup>2</sup>		
Standard print languages	PCLm/PCLmS; URF; PWG		
Print area	Print margins Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area: 216 x 355.6 mm		
Duplex printing	No .		
Сору	•		
Copy speed <sup>5</sup>	Black (A4): Up to 20 cpm		
Copier specifications	Number of Copies; Lighter/Darker; Optimize; Paper; Maximum number of copies: Up to 99 copies; Reduce/Enlarge: 25 to 400%;		
Scan			
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF		

Model	HP LaserJet MFP M141a Printer	HP LaserJet MFP M141w Printer	
Product number	7MD73A	7MD74A	
Scanner specifications	Scanner type: Flatbed; Scan technology: CIS; Scan input modes: Scanning via HP Laser Jet Software Scan or TWAIN-compliant or WIA-compliant software; Twain version: Version 2.1 (Windows 7 or higher); Scan size maximum (flatbed): 216 to 297 mm; Optical scan resolution: Up to 600 ppi		
Scanner advanced features	No No		
Recommended monthly scan volume	250 to 2000		
Scannable area	Maximum media size (flatbed): 216 to 297 mm;		
Bit depth/ Grey scale levels	24 bit / 256		
Processor speed	500 MHz		
Connectivity			
Standard	1 Hi-Speed USB (compatible with USB 2.0 specifications)	1 Hi-Speed USB (compatible with USB 2.0 specifications); 802.11b/g/n (2.4 GHz) Wi-Fi radio + BLE	
Wireless	No	Yes	
Mobile printing capability <sup>6</sup>		HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct Printing	
Supported network protocols		TCP/IP; IPv4; IPv6; IP Direct Mode; LPD; SLP; Bonjour; WS-Discovery; BOOTP/DHCP/AutoIP; SNMP v 1/2/3; HTTP/HTTPS; WS Transfer; FQDN; DNS	
Memory	Standard: 64 MB; Maximum: 64 MB Flash ROM; 64MB DDR1; 32 KB NVRAM		
Media handling			
Number of paper trays	Standard: 1 input tray; Maximum: 1 input tray		
Media types	Plain paper, envelope, postcard, label		
Media size	Custom (metric): 105 x 148 to 216 to 355.6mm; Supported (metric): A4; A5; A6; envelopes (C5, DL); custom		

Model	HP LaserJet MFP M141a Printer	HP LaserJet MFP M141w Printer	
Product number	7MD73A	7MD74A	
Media handling	Standard input: 150-sheet input tray Standard output: 100-sheet output bin		
Media weight	65 to 120 g/m²;		
Input capacity	Tray 1: Sheets: 150; Envelopes: 10 Maximum: Up to 150 sheets		
Output capacity	Standard: Up to 100 sheets Envelopes: Up to 10 envelopes Maximum: Up to 100 sheets		
Compatible operating systems	Microsoft® Windows® 11, 10, 7: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, USB port, Microsoft® Internet Explorer or Edge. Apple® macOS macOS Catalina (v10.15) macOS Big Sur (v11.0) macOS Monterey (v12.0); 2 GB HD Internet required; USB. Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)	From 123.hp.com: HP Smart for Windows 11, 10, Mac, Mobile (Android and iOS); HP Easy Start for Windows 7, From hp.com: Full-solution software and drivers (with installer): Basic-solution software and drivers; HP Easy Start; Product Documentation and Support; HP Print and Scan Doctor; From Mobile OS: See "HP Mobile Printing" (www.hp.com/go/mobileprinting); From In-OS app stores: HP Smart; HP Print Service Plugin; From hp.com for printer administrators: Linux Print Drivers; HP Web JetAdmin Software (HP WS Proxy Agent); Readlris Software	
Compatible network operating systems	Windows Server 2008 R2 64-bit, Windows Server 2008 R2 64-bit (SP1), Windows Server 2012 64-bit, Windows Server 2012 R2 64-bit, Windows Server 2016 64-bit; Linux (For more information see http://developers.hp.com/hp-linux-imaging-and-printing)		
Minimum system requirements	Windows: Microsoft® Windows® 11, 10, 7 SP1: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, USB port, Microsoft® Internet Explorer or Edge.;  Mac Apple® macOS Catalina (v10.15) macOS Big Sur (11.0) macOS Monterey (v12.0); 2 GB HD; Internet required; USB	Windows: Microsoft® Windows® 11, 10, 7 SP1: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer or Edge.;  Mac. Apple® macOS Catalina (v10.15) macOS Big Sur (v11.0) macOS Monterey (v12.0); 2 GB HD; Internet required	
Software included	No CD in box. Download software from hp.com or 123.hp.com		
Security management	Password-protected network embedded Web server	Password-protected network embedded Web server; enable/disable Network ports; SNMPv1/2/3 community password change	
Printer management	HP Printer Assistant (UDC), HP Device Toolbox		
Dimensions and weight			
Printer dimensions (W $\times$ D $\times$ H)	<b>Minimum</b> 360 x 264 x 197 mm; <b>Maximum</b> : 360 x 427 x 347 mm;	<b>Minimum</b> 360 x 264 x 197 mm; <b>Maximum</b> : 360 x 427 x 347 mm;	
Package dimensions (W $\times$ D $\times$ H)	398 x 248 x 306 mm		
Printer weight	5.39 kg		
Package weight	6.9 kg		
Operating environment	Temperature: 15 to 32.5°C; Humidity: 30 to 70% RH		
Storage conditions	Temperature: -20 to 60°C;		
Acoustics	Acoustic power emissions: 6.2 B(A); Acoustic pressure emissions: 51 dB(A)		
Power	Requirements: 2200 - 240V nominal @ +/-10% (min 198V, Max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Typical Electricity Consumption (TEC)*: 0.255 kWh/Week (Energy Star 3.0); 0.259 kWh/Week (Blue Angel); Power supply type: Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty;		
Energy savings feature technology	HP Auto-On/Auto-Off Technology		
Certifications	CISPR32:2012 & CISPR32:2015 /EN55032:2012 & EN55032:2015+AC:2016 - Class B; EN 61000-3-2:2014; EN 61000-3-3:2013; EN 55035:2017; FCC Title 47 (FR, Part 15 Class B/ICES-003, Issue 6 EPEAT® Silver registered in the U.S.; IT ECO Declaration; Blue Angel; EPEAT® Silver India; EPEAT® Silver Australia; EPEAT® Silver Canada; EPEAT® Silver US	CISPR32:2012 & CISPR32:2015 /EN55032:2012 & EN55032:2015+AC:2016 - Class B; EN 61000-3-2:2014; EN 61000-3-2:2013; EN 55035:2017; FCC Title 47 (FR, Part 15 Class B)(ES-003), Issue 6  EPEAT® Silver registered in the U.S.; IT ECO Declaration; Blue Angel; EPEAT® Silver India; EPEAT® Silver Australia; EPEAT® Silver Ganada; EPEAT® Silver US  Telecom compliance: Wireless: EU RED 2014/53/EU; EN 301 489-1 V.2.2.3 / EN 301 489-17: V3.1.1; EN 300 328: V2.1.1 / EN301 893 V2.1.1; FCC Title 47 CFR, Part 15 Subpart C & E / RSS 247 Issue 1, 2015 & RSS 102 Issue 5, 2015; IEC 62311:2007 / EN62311:2008	
Sustainable impact specifications	Recyclable through HP Planet Partners; Contains post-consumer recycled plastic	Recyclable through HP Planet Partners; Contains post-consumer recycled plastic	
Blue Angel compliant		Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies	
Country of origin	Make in Vietnam	<u> </u>	
What's in the box <sup>8</sup>	HP Laser.Jet MFP M141a Printer; Power cord; HP Black Laser.Jet Toner Cartridge (yield: 500 pages); Setup Poster; Reference Guide; Warranty Guide; Flyer	HP LaserJet MFP M141w Printer; Power cord; HP Black LaserJet Toner Cartridge (yield: 500 pages); Setup Poster; Reference Guide; Warranty Guide; Flyer	
Warranty	One-year limited warranty		

#### Footnotes

- <sup>1</sup> Requires the HP Smart app download. For details on local printing requirements see http://www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Subscription may be required; subscription may not be available in all countries. See details at www.hpsmart.com. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores.
- <sup>2</sup> Based on internal HP testing. Average timing estimate based on: 1) downloaded HP Smart app on mobile or desktop device, 2) setting up Shortcut, 3) scanning jobs which have more than 2-3 tasks associated with them (scan to email, save and rename, store to cloud, etc.). Average timing savings comparison based on using printer and desktop scan software to complete similar scanning tasks. Requires the HP Smart app download and supported HP printer. For details on local printing requirements see http://www.hp.com/go/mobileprinting.
- <sup>3</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, host OS, port-monitor, software application, driver, and document complexity.
- 4 USB cable not included; purchase separately.
- <sup>5</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade.

#### Technical specifications disclaimers

- <sup>1</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>2</sup> Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

  <sup>3</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; May require a firmware upgrade.
- <sup>4</sup> Requires the HP Smart app download. For details on local printing requirements see http://www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Instant Ink subscription may be required. Instant Ink not available in all countries. See details at http://www.hptonerservice.com. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. Fax capabilities are for sending a fax only, and may require additional purchase. For more information, see: http://www.hpsmart.com/mobile-fax.

  5 First Copy Out from Ready and Simplex Copy Speed measured using ISO/IEC 29183, Duplex Copy Speed measured using ISO/IEC 24735, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application and document complexity.
- 6 Wi-Fi® is a registered trademark of Wi-Fi Alliance®. Wireless operations are compatible with 2.4 GHz operations only. Learn more at www.hp.com/go/mobileprinting. Wireless performance is dependent upon physical environment and distance from the access point. AirPrint and the AirPrint Logo are trademarks of Apple® Inc. The Mopria® Logo is a registered and/or unregistered trademark of Mopria Alliance, Inc. in the United States and other countries. Unauthorized use is strictly prohibited. Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Instant Ink subscription may be required. Instant Ink not available in all countries. See details at www.hptonerservice.com. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. Fax capabilities are for sending a fax only, and may require additional purchase. For more information, see: www.hpsmart.com/mobile-fax
- 11 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device.
- <sup>3</sup> For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.













Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda hp, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanesenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

https://tehnoteka.rs/p/hp-multifunkcijski-stampac-laserjet-mfp-m141a-7md73a-akcija-cena/