

## Informacije o proizvodu (EN)

SEASONIC napajanje Prime PX 1600W SSR-1600PD2



Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

<https://tehnoteka.rs/p/seasonic-napajanje-prime-px-1600w-ssr-1600pd2-akcija-cena/>

1600 W / 1300 W / 1000 W / 850 W / 750 W / 650 W



## PRIME PX

### SPECIAL FEATURES

- ❖ Super-High Efficiency, 80 PLUS® Platinum Certified
- ❖ Fully Modular
- ❖ Compact ATX Size [140 mm deep] \*
- ❖ Top-Quality 135 mm Fluid Dynamic Bearing Fan
- ❖ Premium Hybrid Fan Control
- ❖ Micro Tolerance Load Regulation (MTLR) [0.5 %]
- ❖ Super Low Ripple Noise [under 20 mV]
- ❖ Cable-free Connection Design
- ❖ Gold Plated High Current Terminal (MB, CPU and PCIe)
- ❖ Multi-GPU Technology Support





\* for 750 W, 650 W



### POWER DISTRIBUTION

| Model         | +3.3 V | +5 V | +12 V   | -12 V | +5 Vsb | Total Power |
|---------------|--------|------|---------|-------|--------|-------------|
| PRIME PX-1600 | 25 A   | 25 A | 133.3 A | 0.5 A | 3 A    | 1600 W      |
|               |        |      | 125 W   | 6 W   | 15 W   |             |
| PRIME PX-1300 | 25 A   | 25 A | 108 A   | 0.3 A | 3 A    | 1320 W      |
|               |        |      | 125 W   | 3.6 W | 15 W   |             |
| PRIME PX-1000 | 25 A   | 25 A | 83 A    | 0.3 A | 3 A    | 1000 W      |
|               |        |      | 125 W   | 3.6 W | 15 W   |             |
| PRIME PX-850  | 20 A   | 20 A | 70 A    | 0.3 A | 2.5 A  | 850 W       |
|               |        |      | 100 W   | 3.6 W | 12.5 W |             |
| PRIME PX-750  | 20 A   | 20 A | 62 A    | 0.3 A | 2.5 A  | 750 W       |
|               |        |      | 100 W   | 3.6 W | 15 W   |             |
| PRIME PX-650  | 20 A   | 20 A | 52 A    | 0.3 A | 3 A    | 650 W       |
|               |        |      | 100 W   | 3.6 W | 15 W   |             |

### CONNECTOR QUANTITY

| Cable         |  |  |  |  |  |  |  |
|---------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
| Model         | Main Power<br>(24P / 20P)<br>610 mm                                                 | EPS 12 V /<br>ATX 12 V<br>(8P / 4P)<br>650 mm                                       | PCI-E<br>(8P / 6P)                                                                  | SATA                                                                                | Peripheral<br>(4P)                                                                  | FDD (4P)                                                                              | 12V HPWR<br>(12+4 Pins)                                                               |
| PRIME PX-1600 | 1                                                                                   | 3                                                                                   | 8                                                                                   | 10                                                                                  | 3                                                                                   | 0                                                                                     | 2                                                                                     |
| PRIME PX-1300 | 1                                                                                   | 2                                                                                   | 8                                                                                   | 14                                                                                  | 5                                                                                   | 1                                                                                     | 0                                                                                     |
| PRIME PX-1000 | 1                                                                                   | 2                                                                                   | 6                                                                                   | 14                                                                                  | 5                                                                                   | 1                                                                                     | 0                                                                                     |
| PRIME PX-850  | 1                                                                                   | 2                                                                                   | 6                                                                                   | 14                                                                                  | 5                                                                                   | 1                                                                                     | 0                                                                                     |
| PRIME PX-750  | 1                                                                                   | 2                                                                                   | 4                                                                                   | 10                                                                                  | 3                                                                                   | 1                                                                                     | 0                                                                                     |
| PRIME PX-650  | 1                                                                                   | 1                                                                                   | 4                                                                                   | 10                                                                                  | 3                                                                                   | 1                                                                                     | 0                                                                                     |



Safety & EMI / EMC



Protection Features: OPP / OVP / UVP / SCP / OCP / OTP

Dimensions: 170 mm (L) x 150 mm (W) x 86 mm (H) (1000 W, 850 W)

140 mm (L) x 150 mm (W) x 86 mm (H) (750 W, 650 W)



Specifications may change without prior notice



Headquarters sales@seasonic.com

USA ssa.sales@seasonic.com

Europe sse.sales@seasonic.com

www.seasonic.com

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda Seasonic, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanесenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

<https://tehnoteka.rs/p/seasonic-napajanje-prime-px-1600w-ssr-1600pd2-akcija-cena/>