

Informacije o proizvodu (EN)

FSP NanoFit 800VA UPS uređaj



Tehnoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

<https://tehnoteka.rs/p/fsp-nanofit-800va-ups-uredjaj-akcija-cena/>

Features

- 600VA / 800VA Standby UPS
- Compact size can be desktop or wall-mounted
- Excellent microprocessor control for high reliability
- Auto restart while AC is recovering
- Simulated sine wave output
- Cold start function
- 2 ports USB charger 5V / 1A (Max.)
- RJ45 surge protection (NanoFit 800 only)
- Optional USB communication port



MODEL	NanoFit 600	NanoFit 800
CAPACITY	600VA / 360W	800VA / 480W
INPUT		
Voltage	220 / 230 / 240Vac	
Acceptable Voltage Range	180-270Vac	
Frequency Range	60Hz / 50Hz (Auto sensing)	
OUTPUT		
Output Voltage	220 / 230 / 240Vac	
AC Voltage Regulation (Batt. Mode)	±10%	
Frequency Range (Batt. Mode)	60Hz or 50Hz ±1Hz	
Transfer Time	Typical 2-6 ms, Max. 10ms	
Waveform (Batt. Mode)	Simulated Sinewave	
BATTERY		
Battery Type & Numbe	12V / 4.5Ah x 1	12V / 5Ah x 1
Typical Recharge Time	8 hours recover to 90% capacity	
INDICATORS		
Line Mode	Green lighting	
Battery Mode	Yellow flashing	
Fault	Red lighting	
ALARM		
Battery Mode	Beeps every 10 seconds	
Low Battery	Beeps every second	
Overload	Beeps every 0.5 second	
Fault	Continuously beeping	
PROTECTION		
Full Protection	Overload, discharge and overcharge protection	
PHYSICAL		
Dimension, D X W X H (mm)	305 x 158.5 x 95 mm	
Net Weight (kgs)	2.6	2.9
ENVIRONMENT		
Humidity	0-90% RH @ 0- 40°C (non-condensing)	
Noise Level	Less than 40dB	

* Product specifications are subject to change without further notice

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda FSP, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Tehnoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Tehnoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Tehnoteka ne odgovara za štetu nanесenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

<https://tehnoteka.rs/p/fsp-nanofit-800va-ups-uredjaj-akcija-cena/>